

G-7SET - Speaker Set



Pair of professional dual-band transceivers, case set, consisting of 2 transceivers with belt clip, 2 clip-on mics with earphones, charger for 2 transceivers, 2 rech. battery packs.

- 8 PMR channels 446 MHz
- 69 LPD channels 433 MHz
- Boost function for a wide operating range
- High-performance rech. batteries for high operational availability
- Manual transmit mode (PTT) or hands-free voice-activated transmit mode (VOX)
- Monitoring function
- Automatic squelch
- Channel scan mode (SCAN)
- CTCSS tones
- Dual watch
- Vibracall function
- Key lock
- Backlit LCD
- Supplied in a robust hard-sided case

Licence-free, please refer to instruction manual on the [MONACOR website](http://www.monacor.dk).

Technical data:

General information

Type	:	hand-held transceiver set
Carrier frequency range	:	446.00625-446.09375 MHz (PMR) 433.075-434.775 MHz (LPD)
Audio frequency range	:	-
Channels	:	8 PMR, 69 LPD
THD	:	-
Dynamic range	:	-
RF S/N ratio	:	-
Operating time	:	-
Admiss. ambient temp.	:	-20 °C to +55 °C
Power supply	:	4 x rech. battery AA size, 800 mAh
Dimensions	:	58 x 195 x 34 mm
Total weight	:	1,203 kg
Connections	:	2.5 mm jack (microphone) 3.5 mm jack (speaker)
Transmitting power	:	500 mW
Operating range	:	≤ 5,000 m
Power supply transmitter	:	-
Width transmitter	:	-
Height transmitter	:	-
Depth transmitter	:	-
Weight transmitter	:	-
Connections transmitter	:	-
Specifications receiver	:	-
Audio signal receiver	:	-
Power supply receiver	:	-
Width receiver	:	-
Height receiver	:	-
Depth receiver	:	-
Weight receiver	:	-
Connections receiver	:	-