



OVERVOLTAGE ARRESTER ELPRO 2 ***QTS 52***

ELPRO 2 is the right overvoltage arrester for all equipment connected to the electricity network. Computer (without modem or fax), TV, video and DVD are typical examples of equipment to be protected by ELPRO 2. However, other types of equipment like copying machine, printer, typewriter, refrigerator, dish washer and washing machine will also have a longer operational life with ELPRO 2 protection.

ELPRO 2 gives complete 3-way protection, i.e. protection between phase and neutral, phase and protective earth (PE) and also between neutral and PE. The clamping voltages are very low even at high surge currents. The max surge current is very high!

ELPRO 2 shall be plugged into an electrical outlet with PE. The green LED shows that all works. In the unlikely event that ELPRO 2 is overloaded the LED is extinguished and the arrester is disconnected. ELPRO 2 must now be exchanged!

Just plug ELPRO 2 in and the installation is completed. Equipment connected to other outlets after ELPRO 2 gets a certain protection.

TECHNICAL SPECIFICATION

Clamping voltage L-PE, N-PE and L-N at 5 kA	< 1000 V _{peak}
Max surge current, pulse 8/20	12 kA
Max pulse energy, pulse 10/1000	330 J
Voltage	250 V AC
Current	16 A

Fulfills EMC-Directive 89/336/EEC and LV-Directive 73/23/EEC.

Made in Sweden.

QUADRA-LAB AB
Box 8047, Avestagatan 35
SE - 163 08 Spånga
Sweden

Phone + 46 (0)8-761 3920
Fax + 46 (0)8-761 3928
e-mail: quadra.lab@quadra.se
www.quadra.se



Rev. A