

MT615



Cobra®

LICENSE-FREE WALKIE-TALKIE
Handfunkgerät
Transceptor
Talkie Walkie

**Communicates with all other
PMR 446 radios**

Up to 5 km range

Compact design with extended
range.

VOX

For hands-free operation.

Call Alert

Provides a recognizable alert for
incoming calls.

Roger Beep

Confirmation tone indicates to
others it's clear to talk.



www.cobra.com



MT615

Features

Benefits

UHF/FM	Ultra-clear long distance reception.
5 KM Range	Up to 5 KM range. (Range will vary depending on terrain and conditions).
8 Channels	Front panel push buttons provide easy access to all 8 channels.
121 Privacy Codes	38 CTCSS (Continuous Tone Coded Squelch System) codes and 83 DCS (Digitally Coded Squelch) codes provide a total of 121 privacy codes. 968 privacy combinations are possible when the 8 channels are combined with the 121 privacy codes.
VOX (Voice Activated Transmission)	User's voice is detected and the radio transmits without the need to press any buttons, freeing the user's hands for other tasks. 5 VOX sensitivity levels allow user to select at which point the radio will detect their voice.
Scan	Allows user to scan either channels, CTCSS privacy codes within a channel, or DCS codes within a channel to locate conversations in progress.
Call Alert (5 selectable tones)	Provides up to 5 easily recognizable call alert tones for incoming calls.
Roger Beep Tone (selectable on/off)	Confirmation tone indicates the completion of the user's transmission, and signals to others it is clear to talk. This feature is selectable and can be turned on or off.
Key Lock	When activated, provides key pad security eliminating accidental channel changes.
Power Saver	A unique circuit extends the life of your batteries. If there are no transmissions within 10 seconds, the unit will automatically switch to battery saver mode.
Auto Squelch	Automatically shuts off weak transmissions or unwanted noise due to terrain or range constraints.
LCD Display	Easy to view display provides the radio's status at a glance.
Speaker/Microphone/Charge Jack	Allows use of "Y" wall mount charger or earphone speaker/microphones (not included) for "hands-free" operation.
Multilingual Manual	Includes a 16 language instruction manual.
Belt Clip	Secures your microTALK radio while on the go.
No Licence or Service Fees	High quality band frequencies with no fees.

Unit Specifications - General

Unit Dimensions: 145 mm H x 59 mm W x 33.56 mm D (5.71" H x 2.32" W x 1.32" D) including antenna	SKU#: MT615	Master Pack Dimension: 305mm L x 377mm W x 160mm H (12.00" L x 14.84" W x 6.30" H)
Unit Weight: 65 g (2.22 oz) Without batteries	UPC#: 0 28377 90951 1	
RF Output: 500 mW	Batteries: 3 AAA per radio (not included)	Master Pack Weight: 3240g (114.29 oz.)
Channels: 8 CH1 = 446.00625 MHz 2 = 446.01875 3 = 446.03125 4 = 446.04375 5 = 446.05625 6 = 446.06875 7 = 446.08125 8 = 446.09375	Masterpack Barcode: 6 0028377 90951 3	*Specifications subject to change without notice* *All dimensions (H x W x D) except where noted*
	Master Pack Qty: 12	
	Package Dimension: 155 mm H x 130.6 mm W x 45.5 mm D (6.10" H x 5.14" W x 1.80" D)	
	Package Weight: 270 g. (9.52 oz.)	

16 Language Manual Includes:



©2011 Cobra Electronics Europe Limited, Dungar House, Northumberland Avenue, Dun Laoghaire, County Dublin, Ireland

Cobra®, microTALK®, Nothing Comes Close to a Cobra® and the snake design are registered trademarks of Cobra Electronics Corporation, USA.

Cobra Electronics Corporation™ is a trademark of Cobra Electronics Corporation, USA.

CEEL™ is a trademark of Cobra Electronics Europe LTD.



* Packaging is made from recyclable materials.