

Tender text

MMX-44

8-channel audio mixer,

with 12 inputs.

- 4 mono input channels, each with gain control, 3-way equalizer, low cut and pan pot
- 4 stereo input channels, each with balance control
- Adjustable aux send output
- Control room function
- Tape record/play connections
- +48 V phantom power, can be switched centrally
- Adjustable headphone output
- Stereo LED level display
- Power is provided via enclosed power supply

Specifications:

No. of channels	8
No. of inputs	12
Mic input	0.5 mV, bal., 4 x 3-pole XLR
Line input	10 mV, bal. (stereo), 4 x 6.3 mm jack L/R 1 mV (mono), 4 x 6.3 mm jack
Tape (play)	100 mV, 1 x RCA L/R
Master output	650 mV, 1 x 6.3 mm jack L/R
Aux output	9.5 V, 1 x 6.3 mm jack
Control room	2 V, 1 x 6.3 mm jack L/R
Tape (rec)	650 mV, 1 x RCA L/R
Headphones	$\geq 8 \Omega$, 1 x 3.6 mm jack
Frequency range	20-20,000 Hz
THD	< 0.05%
S/N ratio	> 74 dB
Crosstalk	-63 dB
Equalizer bass	± 15 dB/80 Hz
Equalizer midrange	± 15 dB/2.5 kHz
Equalizer treble	± 15 dB/12 kHz
Phantom power	+48 V
Power supply	via encl. power supply
Admiss. ambient temp.	0-40 °C
Width	280 mm
Height	50 mm
Depth	260 mm
Weight	2.2 kg

Brand: IMG STAGELINE

Type: MMX-44

Quantity: 1

Packing dimensions: 0.13 x 0.33 x 0.43 m

Gross weight:

Net weight:

Item weight (w/o accessories):