


VOLTMETER WITH 3 DIGIT LED DISPLAY

COM-VM330



This small mini voltmeter for voltages from 3 to 30 V has a 3 digit 7-segment display (0.36 Inch). The measured value can be displayed with 1 or 2 decimal digits and is refreshed every 0.3 seconds. This measurement device is outstanding by its very low power consumption of less then 30 mA and can be mounted using the 2 mounting holes.

If a separate 3 V power supply is connected, voltages from 0 to 30 V can be measured.



MAIN FEATURES	
Model	VM330
Special features	power supply via measure- ment voltage, Reverse polarity protection
Display	0.36 inch LED 7-segment display, shows 1 or 2 deci- mal digits
Dimensions	33 x 14.5 x 9.5 mm
Items delivered	DC mini voltmeter with 2 wires each 18 cm

FURTHER SPECIFICATIONS	
Operating voltage	3 V DC (via measurement voltage)
Measurement voltage	3 - 30 V DC
Measurement accuracy	0.1 %
Current consumption	< 30 mA
refresh rate	approx. 300 ms
input resistance	>100 kΩ
Environment temperature	-10 to 65°C

FURTHER DETAILS	
Article No.	COM-VM330
EAN:	4250236821955
Customs Tariff No.	8473302000

Published: 17.08.2021

www.joy-it.net SIMAC Electronics GmbH, Pascalstr. 8, 47506 Neukirchen-Vluyn