

## Satellite Power Inserter | 2x F Output | Insertion loss: -5 dB

### General information

Power supply unit for antenna amplifiers.

### Specifications

Colour:	White
Number of inputs:	1
Power consumption in operating mode:	5.5 W
Insertion loss:	5 dB
Number of outputs:	2
Application:	Satellite
Connector type:	F-connector
Power plug:	Euro / Type C (CEE 7/16)
Impedance:	75 Ohm
Frequency range:	40 - 862 MHz
Input voltage:	230 VAC 50/60 Hz
Appliance:	Power Supply

### Package contents

Power inserter



### Sales information

Order code: **SPIN100WT**  
 Product description: Satellite Power Inserter | 2x F Output | Insertion loss: -5 dB  
 Packaging: Bulk  
 Brand name: Nedis



Quantity	LxWxH (mm)			Weight
1	110 mm	170 mm	45 mm	356 g
10	260 mm	125 mm	285 mm	3770 g
50	295 mm	635 mm	280 mm	19470 g